



Meinberg Funkuhren

Lange Wand 9 31812 Bad Pyrmont, Germany Phone: +49 (5281) 9309-0

Fax: +49 (5281) 9309-30 https://www.meinbergglobal.com

info@meinberg.de

GPS167MP: The ready-to-operate GPS systems built up in rackmount slimline modular cases.

The ready-to-operate systems GPS167-MQ/F4/MP (GPS167-MQ/LCD/F4/MP) and GPS167/ MP (GPS167/LCD/MP)

The satellite receiver clock GPS167 provides extremly precise time as well as pulses and frequency outputs. The clock has been developed for applications where conventional radio controlled clocks cannot meet the increasing requirements in precision and reliability. High precision available 24/7 around the world is the main feature of this high-quality system which receives its information from the satellites of the Global Positioning System.

Important Note

This product is no longer available. We will of course continue to provide support for units that have already been purchased and are still in use. Please contact our [1] Sales Team for further details.

Key Features

- 2 time trigger inputs
- Pulses per second and per minute
- LC Display for configuration (.../LCD/... types only)
- 2 RS-232 interfaces
- integrated power supply (85 ... 264VAC)
- Optional (only .../F4/... models): four frequency outputs 2.048MHz direct, 3.0Vpp into 50 Ohm 2.048MHz switched, 3.0Vpp into 25 Ohm 10MHz direct, 3.0Vpp into 50 Ohm 10MHz switched, 3.0Vpp into 25 Ohm
- alarm relay output, changeover contact
- Including GPS antenna, 20m standard cable and manual on USB key



Description

The ready-to-operate systems GPS167-MQ/F4/MP (GPS167-MQ/LCD/F4/MP) and GPS167/MP (GPS167/LCD/MP) are built up in 19" slimline modular cases (1U).

The frequency locking of the master oscillator to the GPS system enables the module GPS167 to generate fixed and programmable standard frequencies with high accuracy and stability. Various oscillator options allow the cost efficient implementation of different requirements concerning the accurracy of the outputs. The pulse generator of GPS167 generates pulses per second and per minute. As an option three programmable outputs are available. The pulses are synchronized to UTC second.

Up to four serial interfaces are available for sending time strings. These ASCII telegrams include information regarding time, date and status of the GPS receiver. The module provides two inputs for measurement of asynchronous time events. These capture events are shown on the LC display (only LCD models) and can be read via a serial interface.

The front panel of LCD models integrates a LC display that shows information regarding the GPS receiver in different menus. In combination with four push buttons it is also used to setup all configurable parameters.

The ../F4/.. models come with E1/T1 frequency outputs and are widely used in the telecommunicaton sector.

A powerful and feature-rich software called GPSMON is available for configuration and monitoring of your Meinberg GPS receivers.

Characteristics

Receiver Type	6 channel GPS C/A-code receiver
Status Indicators	Fail-LED shows that the internal timing has not been synchronized or that a system error occurred Lock-LED shows that the calculation of the position has been achieved after reset
Type of Antenna	Included [2]GPSANTv2 antenna with innovative downconverter technology that allows transmission routes of up to 300 m using RG58 cable, 700 m using RG213 cable, and 1100 m using H2010 Ultraflex cable
Display	LC-Display, 2 x 40 Characters, with Backlight
Control Elements	Configuration occurs by using the enclosed monitoring software, connected to the system via the serial interface COM0 in the front panel/LCD/ only Configuration occurs via the 2x40 character front panel LC display or by using a monitoring software, connected to the system via the serial interface COM0 in the rear panel.
Synchronization Time	Max. 1 minute in normal operating conditions Max. 25 minutes (average 12 minutes) upon first initialization or in the absence of saved satellite data
Interface	Two independent serial RS-232-interfaces, menu configurable



Serial Time String Output	Baud rate: 300, 600, 1200, 2400, 4800, 9600, 19200 Baud Data format: 7N2, 7E1, 7E2, 8E1, 8N1, 8N2 Time telegram: [3]Meinberg Standard Time String, SAT, Uni Erlangen (NTP), SPA, Sysplex, RACAL, NMEA0183 (RMC,GGA,ZDA), Meinberg GPS, COMPUTIME, ION oder [4]Capture String
Time Trigger Inputs	Resolution: 100 nsec, triggered by falling TTL slope Time of trigger event readable via RS232-interface
Antenna Connector	Type-N connector
Backup Battery Type	Upon loss of power supply to card, the hardware clock runs independently using the on-board quartz oscillator. Almanac data remains stored in battery-backed RAM Life time of lithium battery min. 10 years
Supported Time String Formats	Meinberg Standard Timestring, Uni Erlangen Timestring, SYSPLEX Timer, NMEA, Computime, ABB-SPA, SAT, Arbiter
Firmware	Flash-EPROM, bootstrap loader
Form Factor	19" aluminium case (1U) Schroff Multipac
Power Supply Unit	Standard PSU: 85 264VAC, 47 63Hz Several other power supply units (even for DC power supply) are available upon request.
Physical Dimensions	485mm x 45mm x 305mm
IP Rating	IP20
Supported Temperature	Operational: 0 - 50 °C (32 - 122 °F) Storage: -20 - 70 °C (-4 - 158 °F)
Supported Humidity	Max. 85 % (non-condensing) at 40 °C
Contents of Shipment	Included in delivery is our [2] GPS antenna incl. converter unit and 20 m GPS antenna cable (RG58).
Warranty	Two-Year Warranty

Manual

The English manual is available as a PDF file: [5] Download (PDF)

Links:

- [1] mailto:sales@meinberg.de
- $\hbox{\cite{thm}$} \begin{tabular}{l} [2] https://www.meinbergglobal.com/english/products/gps-antenna-converter.htm \end{tabular}$
- [3] https://www.meinbergglobal.com/english/specs/timestr.htm
- [4] https://www.meinbergglobal.com/english/specs/capstr.htm
- $\hbox{[5] https://www.meinbergglobal.com/download/docs/manuals/english/167_1he_lcd.pdf}$