



Meinberg Radio Clocks

Lange Wand 9
31812 Bad Pyrmont, Germany
Phone: +49 (5281) 9309-0
Fax: +49 (5281) 9309-30
<https://www.meinbergglobal.com>
info@meinberg.de

LANTIME M320: NTP Server in 1U Case for Server Rackmount

[1] The Meinberg LANTIME M320 time server is used to provide highly accurate time to networks of all sizes. They synchronise all systems that are either NTP or SNTP compatible. As a reference time source, this NTP system typically use a built-in Meinberg reference clock or a compatible external time source (operating in stratum 1 mode). Up to 7 external NTP servers can also be set as time reference (operation as stratum 2 server).

Key Features

- Selectable Reference Time Sources: GPS: Satellite receiver for the Global Positioning System GNS: Combined GPS/GLONASS/Galileo/BeiDou satellite receiver, can also be used for mobile applications GNS-UC: GPS and Galileo Satellite Receiver with Up-Converter for Meinberg GPS Antenna/Converter GNM: GPS/GLONASS/Galileo/BeiDou - Multi Band satellite receiver (L1/L2 frequency band) for simultaneous reception of all satellite systems PZF: DCF77 correlation receiver for middle europe MSF: Long wave receiver for Great Britain TCR: Time code receiver for IRIG A/B, AFNOR or IEEE1344 codes MRS: (GPS, PPS, 10MHz, NTP): Multi Reference Source - several reference sources, adjustable following priority of signal RDT: (external PPS or NTP): Time Server without internal receiver module
- Synchronizes NTP-compatible clients with support for NTP, SNTP, and NTS - Network Time Security
- Web interface that is both powerful and easy to use
- Backlit LCD panel and function keys for local configuration
- Frequency signals and industry-specific sync signals via additional optional outputs
- USB port for installation of firmware updates, backup/restore of configuration and log files, and disabling/enabling access to front panel controls
- Command line interface for advanced power users with absolute control over every facet of the server's functionality
- Comprehensive networking support, including full HTTPS encryption for Web Interface and REST API with TLS certificate management
- Support for syslog, SNMP, and SMTP for comprehensive event logging, network integration, and notification functionality
- GNS models include Multi-GNSS antenna for reception of GPS, Galileo, BeiDou, and GLONASS signals
- GPS and GNS-UC models include Meinberg IF antenna of reception of GPS signals and, with GNS-UC models, also Galileo signals

Description

A large display shows the state of the NTP subsystem.

The configuration of the system can be done by using a standard web browser to access the extensive but straightforward html interface. Alternatively a text based and menu driven setup utility can be started from the shell prompt after logging into the unit via Telnet or SSH.

Because of its modular system architecture it is possible to equip this LANTIME time server with up to six ethernet ports, even fiber optic network ports and one or three Gigabit Ethernet ports are available as an option.

Oscillator Options

The LANTIME M320 comes standard with a "TCXO" (Temperature Controlled Crystal Oscillator) which provides excellent holdover performance in case your time server loses synchronization with its upstream reference for some reason. On request the LANTIME M320 can also be delivered with a more powerful holdover solution (OCXO LQ/SQ/MQ/HQ/DHQ) (see oscillator overview).

MRS - Multi Reference Source capable

In addition, this NTP time server can also be synchronized via other signal sources as GNSS or NTP. PPS, 10 MHz, IRIG Time Codes are also available for our M320/MRS model.

The MRS version comes with a high quality OXCO and is designed to act as a reliable time source in applications where no antenna can be installed. The internal OCXO-HQ can be fully disciplined by utilizing one or more remote NTP time servers. Thus, a LANTIME MRS time server can be run in fully independent mode in environments where no source of time is available.

Configuration and Monitoring

The configuration of the system can be managed by using a standard web browser for accessing the extensive but straightforward HTML web interface. Alternatively a text based and menu driven setup utility can be started from the shell prompt after logging into the unit via Telnet or SSH.

Characteristics

Status Indicators	Four bicolor LEDs indicating: <ul style="list-style-type: none"> - Reference time status - Time service status - Network link status - Alarm states
Display	LC-Display, 2 x 40 Characters, with Backlight
Control Elements	Eight push buttons to set up basic network parameters and to change receiver settings
Frequency Outputs	10 MHz via female BNC connector, TTL into 50 Ohm Accuracy depends on oscillator (standard: TCXO), look at [2]oscillator list
Pulse Outputs	Pulse Per Second (PPS), TTL level, pulse width: 200 ms
Accuracy of Pulse Outputs	Depends on oscillator option: < ±50ns (OCXO SQ, OCXO MQ, OCXO HQ, OCXO DHQ)
Interface	Two independent serial RS-232 interfaces, menu configurable (in case of RDT models without internal receiver - the serial interfaces will be used as reference input).
Optional Output Signals	Additional Output Options:: This LANTIME NTP server comes with many additional outputs options: PPS, 10MHz, programmable pulse outputs (PPS, PPM, PPH, DCF_MARK ...), IRIG modulated and unmodulated time code, T1 / E1 telecom signals, Frequency Synthesizer - to name just a few. Contact us for your specific device configuration.
Serial Time String Output	COM 0: Baudrate: 300, 600, 1200, 2400, 4800, 9600, 19200 Baud Data Format: 8E1, 8E2, 8N1, 8N2, 8O1, 7E1, 7E2, 7N2, 7O1, 7O2 Time Telegram: [3]Meinberg Standard Time String , SAT, NMEA RMC, Uni Erlangen (NTP), COMPUTIME, Sysplex, [4]Capture String , SPA, RACAL, Meinberg GPS, NMEA GGA, NMEA RMC GGA, NMEA ZDA, ION, 6021 or IRIG-J
Relay Outputs	Error Relay <ul style="list-style-type: none"> * Max. Switching Voltage: 125 V DC / 140 V AC * Max. Switching Current: 1 A * Max. Switching Power: 30 W DC / 60 VA AC * Response Time: Approx. 2 ms

Network Interface	Standard: 2 x 10/100 MBit with RJ45 connector Available Options: * 2 or 4 x additional 10/100 MBit with RJ45 * 2 additional 100 MBit with fibre optic SC connector, duplex * 1 x 10/100 MBit and 1 x 10/100/1000 MBit with RJ45 or 1 x 10/100 MBit and 3 x 10/100/1000 MBit with RJ45 jack
Universal Serial Bus (USB) Ports	1x USB port on front panel for: - installing firmware upgrades - performing backups and restoration of configuration files - copying security keys - locking & unlocking front buttons
Operating Voltage	Standard: UN = 100-240 V AC (50/60 Hz) / 100-200 V DC Umax = 90-265 V AC / 90-250 V DC Available DC variants: UN = 100-200 V DC, 24 V DC and 24-48 V DC Umax = 90-250 V DC, 10-36 V DC and 20-60 V DC Redundant power supply combinations available
Form Factor	19 inch multipac metal case 1U/84HE
CPU	 * Intel® Atom
Operating System of the SBC	Custom LANTIME OS based on Linux 4.x LTS Kernel.
Network Protocols OSI Layer 4 (Transport Layer)	TCP, UDP
Network Protocols Authentication	A LANTIME NTP server supports Radius, TACACS+ and LDAP(S) as external authentication methods. * TACACS+: Terminal Access Controller Acc-Control System * Radius: Remote Authentication Dial In User Service * LDAP/LDAPS: Lightweight Directory Access Protocol

Network Protocols OSI Layer 7 (Application Layer)	Telnet, FTP, SSH (including SFTP, SCP), HTTP, HTTPS, syslog, SNMP
Internet Protocol (IP)	IPv4, IPv6
Network Autoconfiguration Support	IPv4: Dynamic Host Configuration Protocol - DHCP (RFC 2131) IPv6: Dynamic Host Configuration Protocol - DHCPv6 (RFC 3315) and Autoconfiguration Networking - AUTOCONF (RFC 2462)
Network Time Protocol (NTP)	NTP v2 (RFC 1119), NTP v3 (RFC 1305), NTP v4 (RFC 5905) SNTP v3 (RFC 1769), SNTP v4 (RFC 4330) MD5 / SHA-1 Authentication and Autokey Key Management
Parallel Redundancy Protocol (PRP)	PRP (IEC 62439-3)
Time Protocol (TIME)	Time Protocol (RFC 868)
IEC 61850	Synchronization of IEC 61850-compliant devices using SNTP
Hypertext Transfer Protocol Secure (HTTPS)	HTTP(S) for web interface and REST API access
Secure Shell (SSH)	SSH v1.3, SSH v1.5, SSH v2 (OpenSSH)
Telnet	Telnet (RFC 854-RFC 861)
Simple Network Management Protocol (SNMP)	SNMPv1 (RFC 1157), SNMPv2c (RFC 1901-1908), SNMP v3 (RFC 3411-3418)
Supported Temperature	Operational: 0 - 50 °C (32 - 122 °F) Storage: -20 - 70 °C (-4 - 158 °F)
Supported Humidity	Max. 85 % (non-condensing) at 40 °C
Contents of Shipment	Included in delivery is a Meinberg outdoor antenna incl. mounting kit, pre-assembled antenna cable (except TCR and RDT models).
Technical Support	Meinberg offers free lifetime technical support via telephone or e-mail.
Warranty	Three-year warranty
Firmware Updates	Firmware is field-upgradeable, updates can be installed directly from the unit or via a remote network connection. Software updates are provided free of charge for the lifetime of your Meinberg product.
RoHS Status of Product	This product is fully RoHS-compliant.
WEEE Status of Product	This product is handled as a B2B (Business to Business) category product. To ensure that the product is disposed of in a WEEE-compliant fashion, it can be returned to the manufacturer. Any transportation expenses for returning this product (at end-of-life) must be covered by the end user, while Meinberg will bear the costs for the waste disposal itself.

Additional Information

Additional information about the Meinberg LANTIME family of NTP time servers and other LANTIME models can be found on the [5][LANTIME overview page](#) .

Manual

There is no online manual available for this product.: [6][Contact us](#)

Links:

[1] <https://www.meinbergglobal.com/english/products/>

[2] <https://www.meinbergglobal.com/english/specs/gpsopt.htm>

[3] <https://www.meinbergglobal.com/english/specs/timestr.htm>

[4] <https://www.meinbergglobal.com/english/specs/capstr.htm>

[5] <https://www.meinbergglobal.com/english/products/ntp-time-server.htm>

[6] <mailto:info@meinberg.de>